

ON/OFF electronic expansion valve driver

התקנה על מסילה DIN 4

XEV11D

The XEV11D controller is equipped with simple LEDs to signal the working state, it does not have a full display but can be easily programmed using the KB1-PRG hand held programming keyboard. The keyboard is only used during the programming phase; during the normal operation XEV11D works on its own.



מאפיינים טכניים

24, 110, 230Vac	אספקת מתח
ON/OFF	סוגי שסתומים

כניסות רגשים

4÷20mA/0÷5V configurable	לחץ יניקה
Pt1000/NTC configurable	טמפרטורת יניקה

כניסות דיגיטליות

present	ללא מתח
present	מתח גבוה

יציאות / מגעים

8A configurable	אזעקה
-----------------	-------

יציאות אחרות

present	יציאת מפתח תכנות / ערכת תכנות
KB1-PRG	יציאת פנל הפעלה מרחוק
RS485	יציאה תקשורת סריאלית
present	

אחר

optional	ציפצוף פנימי
present	

מדידות

±0.7°C ±1digit	דיוק
----------------	------

כללי

Self extinguishing ABS	מארז
6VA max	צריכת אנרגיה
EEPROM memory	אגירת נתונים
0°C÷60°C 32°F÷140°F	טמפרטורת עבודה
-25°C÷60°C -13°F÷140°F	טמפרטורת אחסון

20÷85%	לחות יחסית
0.1 °C or 1 °C or 1 °F	רזולוציה
Screw-terminal block <2.5mm ²	חיבורי מודול חיצוני